

Lumini-LED Retrofit

Job/Location: _____
 Contractor: _____ Model Number: _____
 Prepared By: _____ Date: _____



LED RETROFIT ADAPTORS

Available bases for DCB, Intermediate, and Medium. For 120VAC or UDC applications. Less than 2 watts.

MODEL OPTIONS

LUMINI-I for an Intermediate based **LUMINI** 120VAC.

LUMINI-M for a Medium based **LUMINI** 120VAC.

LUMINI-D for a DC Bayonet based **LUMINI** 120VAC.

LUMINI-HW for a Hard Wired 120VAC or 347VAC **LUMINI**.

OPERATION

Universal emergency circuit (UDC): 6VDC to 24VDC. 120VAC or 347VAC Input (347V is for hard wired version only).

DIMENSIONS

Exit 11 3/8" (length) x 1" (width) x 7/8" (height)
 Sortie 16 3/8" (length) x 1" (width) x 7/8" (height)
 B6L 26 3/8" (length) x 1" (width) x 7/8" (height)

1 year warranty

ORDERING INFORMATION

Series	Base	Size	Colour	Operation
LUMINI	I (Intermediate)	Blank (Exit)	Blank (Red)	UDC (Universal 6-24VDC)
	M (Medium)	SORTIE (Sortie)	G (Green)	120V (120VAC input)
	D (DC Bayonet)	B6L (Bilingual)	W (White)	

EXAMPLE: LUMINI-M-UDC

DESCRIPTION: Lumini LED Retrofit, medium base, Exit sign, Universal 6-24VDC

Series	Base	Size	Colour	Operation
LUMINI	HW (Hard Wired)	EXIT	Blank (Red)	UDC (Universal 6-24VDC)
		SORTIE	G (Green)	120V (120VAC input)
		B6L	W (White)	*347V (347VAC input)

NOTE: *347V is available in Hard Wired base only

EXAMPLE: LUMINI-HW-EXIT-347V

DESCRIPTION: Lumini LED Retrofit, hard wired, exit sign, red, 347VAC input