

Enerlites®

30-MINUTE 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06A-J



DESCRIPTION

The ENERLITES HET06A-J is an in-wall timer switch with 7 buttons. The buttons offer 6 preset countdown times ranging from 1 minute to 30 minutes and one manual ON/OFF button that can override the timer. The timer switch has a blue LED indicator that blinks during selection, then turns off. This device can work with incandescent, fluorescent, and LED lights as well as fans.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Replace standard light or fan single pole switch
- Blue LED indicator remain off when the switch is not in use
- Ground Wire Required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	6.4A
Tungsten	800W
Electronic Ballast	800VA
Motor	1/4 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Laundry Room
- Pantry
- Basement
- Garage
- Home Spa

SPECIFICATION SUBMITTAL

Job Name Job Number

Notes