

# Installation Instructions

NELOCAC Series

ELO LED Surface Mount Luminaires

READ PRIOR TO ATTEMPTING INSTALLATION  
ALWAYS TURN OFF MAIN POWER BEFORE INSTALLATION  
INSTALLATION SHOULD BE CARRIED OUT BY YOUR LOCAL ELECTRICIAN

**WARNING** - Risk of fire. Use 120VAC 50/60Hz circuits.

**WARNING** - Risk of shock. An electric current can cause painful shock or serious injury unless handled properly. For your safety, always remember to turn off power supply at the fuse or circuit breaker box before you install the fixture and ground the fixture to avoid potential electric shocks and to ensure reliable starting.

**WARNING** - Risk of cuts. Some metal parts in the fixture may have sharp edges. To prevent cuts and scrapes, wear gloves when handling the parts.

**WARNING** - This fixture is designed for use in a circuit protected by a fuse or circuit breaker. It is also designed to be installed in accordance with local electric codes. If you are unsure about your wiring, consult a qualified electrician or a local electrical inspector, and check your local electric code.

**AVERTISSEMENT** - Risque d'incendie. Utiliser des circuits 120VAC 50/60Hz


**AVERTISSEMENT** - Risque de choc. Un courant électrique peut causer des chocs douloureux Pour votre sécurité, vérifiez l'alimentation du boîtier du disjoncteur avant d'installer le projecteur et de le mettre à la terre pour éviter tout risque choc et assurer un démarrage fiable.

**AVERTISSEMENT** - Risque de coupure. Certaines pièces métalliques de l'appareil peuvent avoir des arêtes vives. Pour éviter les coupures et les éraflures, portez des gants lors de la manipulation des pièces.

**IMPORTANT** - Cet appareil est conçu pour être utilisé dans un circuit protégé par un fusible ou un disjoncteur. Il est également conçu pour être installé conformément aux codes électriques locaux. En cas de doute sur votre câblage, consultez un électricien qualifié ou un inspecteur en électricité local et vérifiez votre code d'électricité local.



PACKAGING CONTENTS




NELOCAC - ELO



Junction Box Screws (2)



Wire Connectors (2)







Plugs (4)



Bracket (1)

## SURFACE MOUNTING INSTALLATION:

1. Fix bracket on the junction box using screws. (Figure 1)
2. Connect the wires from junction box to the wires on fixture according to local and national electrical codes. (Figure 2)
3. Fix the fixture on the bracket using provided plugs (Figure 3)
4. Place the metal color ring (optional) on the fixture, an internal magnet will hold the ring. (Figure 4)



## RETROFIT INSTALLATION (5" OR 6" HOUSING): **NOTE: RETROFIT KIT REQUIRES HOUSINGS WITH TORSION SPRING HOLDERS**

1. Place Lamp Replacement Marking in housing where visible during installation.
2. Remove the existing trim and lamp from recessed housing. Secure torsion springs onto the ELO fixture using screws provided, adjust the width to fit in 5" or 6" can. (Figure 5)
3. Insert the wires to the orange connector to connect White to White and Black to Black wires. Screw E26 socket adapter into socket in the housing. (Figure 6)
4. Squeeze the torsion springs to insert the fixture into the housing. (Figure 7)
5. Place the metal color ring on the fixture, an internal magnet will hold the ring. (Figure 8)

