

Project	
Date	
Prepared by	
Model #	FLS1-804TR-1

FLS1-SERIES ULTRA-SLIM FLOOD LIGHT

OVERVIEW

The FLS1 Ultra-Slim Flood Light series is an ultra low-profile LED flood light designed for mounting on poles or walls to illuminate building perimeters, walkways, and landscapes or for wall graze and wall wash accent lighting.



PRODUCT HIGHLIGHTS

- Ultra low-profile and light-weight design lends to versatility
- Durable polycarbonate lens
- Easily mounts on waterproof J-box
- 5 year warranty














OPTICAL SPECIFICATIONS					
Lumen Output (lm) ₁	7716 lm	Beam Angle (°) ₁	95°		
CCT (K) 1	4000K	Projected Lifetime (L ₇₀)	50,000 hours		
CRI (Ra) ₁	82.6	Lumen Maintenance Factor	70%		
Efficacy (lm/W) ₁	104.37 lm/W				
ELECTRICAL SPECIFICATIONS					
Power	80W	Current Draw at 120V _{AC} (A) ₂	0.68A		
Apparent Power (VA)	80VA	Current Draw at 208V _{AC} (A) ₂	0.38A		
System Wattage (W)	73.936W	Current Draw at 240V _{AC} (A) ₂	0.33A		
Input Voltage	100-277V	Current Draw at 277V _{AC} (A) ₂	0.27A		



PREMISE**LED**.COM

CONSTRUCTION		APPROVALS AND LISTINGS			
Housing Material	Die-cast aluminum	DLC	PLPA9ELUHILT		
Housing Color	Dark Bronze				
Lens Material	Polycarbonate	Wet Location Rated	Yes		
Dimensions (inch/mm)	220 mm (L) x 320 mm (H) x 68 mm (D) 8.66" (L) x 12.6" (H) x 2.68" (D)	Wet Location nateu			
Installation Method	Yoke	UL/ETL	cETLus		
Operation Range (°F/°C)	-40°C to 40°C -40°F to 104°F	UL/ETL File Number	4008363		
IP Rating	IP65				
Warranty	5 Years				
LED AND DRIVER SPECIFICATIONS					
LED (Brand)	SMD	Output Voltage (VDC)	36±2V		
LED Design Origin	Korea	Power Factor	0.894		
LED Type	2835	THD	21.72%		
Dimmable	No				
CANDELA		ILLUMINANCE AT A DISTANCE			





Due to the special conditions of manufacturing, the typical data of optical specifications can only reflect statistical figures and do not necessarily correspond to the actual parameters of each single product which could differ from the typical data. Exceeding maximum ratings for input voltage and current will cause hazardous overload and will likely destroy the LED fixture.

Refer to Warranty Terms & Conditions available at premiseled.com/warranty