

36W LED Retrofit Lamp

Order Code: LP12893



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Features & Benefits

- Replaces MH or HPS up to 175W*
- Replaces CFL up to 85W*
- 5 year warranty
- Universal burn position
- · Easy installation
- Reduced maintenance costs
- *Note: It is the customer's responsibility to verify that the lamp compartment meets the minimum required lamp compartment dimension of 8 " diameter by 11" long.

Applications

- Post top
- Wall pack
- Area Lighting
- Flood lighting
- · Garage lighting
- · General illumination

Notes

- The use of an external surge protection device is recommended.
- Operating temp. range between -40°F and 122°F (-40°C and 50°C).
- Suitable for use in dry and damp environments.
- Suitable for use in portable, surface mounted and ceiling luminaires.
- Suitable for use in open and enclosed luminaires with minimum lamp compartment dimensions of 8 inch diameter x 11 inch deep.
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire.
- Lamps have clear polycarbonate cover lenses

Product Performance	
Input Power (W)	36
Initial Lumens	4320
Lumens/Watt	120
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours	50000
Minimum Lamp Compartment Size	8" Dia by 11" long
Dimming	No
Operating Temperature Range	-40°F to 122°F (-40°C to 50°C)

Physical Characteristics	
Base Type	Medium, (E26)
Overall Length A	9.25" (235mm)
Diameter B	3.66" (93mm)
Weight	1.8 lbs (816 g)

Electrical Characteristics	
Input Voltage Range	100V-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	>0.90
THD	<20%

regarator) quarrications
cULus Listed
cULus Classified – Certified to UL 1598C

Accessories

SP12714 - 120-277V Surge Protector


Regulatory Qualifications








Venture 36W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606 Fax: (800) 451-2605 2451 Enterprise Parkway East Twinsburg, Ohio 44087 USA E-mail: venture@adlt.com VentureLighting.com

