

Omni-Bus Devices Power Consumption

Product Code	Details	Power supply	Standby ON	Maximum Draw when On
110A00-1	Omni-Bus Dimmer DIN Rail	15-24VDC	16mA	20mA Max
110A00-2	Omni-Bus Universal Dimmer DIN Rail	15-24VDC	16mA	20mA Max
111A00-1	Omni-Bus Power Switch DIN Rail	15-24VDC	20mA	50mA Max
112A00-1	Omni-Bus 4-Channel Relay Module DIN Rail	15-24VDC	19mA	100mA Max
113A00-1	Omni-Bus 1-Button Wall Switch-White	15-24VDC	13mA	30mA Max
113A00-2	Omni-Bus 1-Channel Wall Mount Remote Control	Battery	N/A	N/A
113A00-3	Omni-Bus 2-Button Wall Switch-White	15-24VDC	18mA	30mA Max
113A00-4	Omni-Bus 2-Channel Wall Mount Remote Control	Battery	N/A	N/A
113A00-5	Omni-Bus 3-Button Wall Switch-White	15-24VDC	21mA	30mA Max
113A00-6	Omni-Bus 3-Button Wall Switch-Brushed Stainless	15-24VDC	47mA	50mA Max
113A00-7	Omni-Bus 3-Channel Wall Mount Remote Control	Battery	N/A	N/A
113A00-8	Omni-Bus 6-Button Wall Switch-White	15-24VDC	23mA	50mA Max
113A00-9	Omni-Bus 6-Button Wall Switch-Brushed Stainless	15-24VDC	76mA	80ma Max
114A00-1	Omni-Bus 6-Channel Universal Switch Interface Module	15-24VDC	18mA	40ma Max
115A00-1	Omni-Bus RF Transceiver DIN Rail	15-24VDC	21mA	50mA Max
116A00-1	Omni-Bus USB Programming Interface Unit	15-24VDC	N/A	50mA Max
117A00-1	Omni-Bus Interface Translator DIN Rail	16-24VDC	56mA	250mA Max
118A00-1	Omni-Bus DALI Gateway DIN Rail	15-24VDC	29mA	80mA Max
119A00-1	Omni-Bus Splitter Box 3-Way	N/A	N/A	N/A
120A00-1	Omni-Bus Splitter Box 8-Way DIN Rail	N/A	N/A	N/A
123A00-1	Omni-Bus Bus Power Supply 2.5A DIN Rail	24VAC	N/A	2A Max
124A00-1	Omni-Bus Bus Power Supply Interface 2A DIN Rail	24VAC	N/A	20mA Max
125A00-1	Omni-Bus 6-Channel Key Ring Remote Control	Battery	N/A	N/A
125A00-2	Omni-Bus 16-Channel Key Ring Remote Control	Battery	N/A	N/A
126A00-1	Omni-Bus Scene Controller DIN Rail	15-24VDC	29mA	80mA Max