LED UNDERCABINET LIGHTING

Surface/Recessed LED-HU-33-3W-WH-27K

LED-HU-33-3W-_A_-B_

SERIES	(A)	(B)COLOR TEMP		
LED-HU-33-3W	SN- Satin Nickel PB- Polish Brass WH- White	BK- Black CH- Chrome BZ- Bronze	□ 27K	

Description

- Aluminum body
- May be mounted recessed or surface (Mounting ring supplied)
- Includes: Three fixtures with quick connectors and mounting hardware. One 9W LED driver with 6' cord.
- Ceiling opening is 2-1/8"
- Outside diameter is 2-5/8"
- 3W LED Warm White 180 lumens
- Puck light kit replacement driver
- LED-HU-30-DR-9W (9W Driver. Up to 3 fixtures max)
- 2700K Color Temperature









The following driver can be sold seperately.

		# of Puck Lights				Wattage Per	Expected Lumen		
Description	Input	Input Current	Minimum	Maximum	Wattage	Puck Light	Output/Fix	Connector's Qty.	
8W/350mA LED Driver	120V	.350mA	1	6	8	1	80LM	6	
9W/700mA LED Driver	120V	.700mA	1	3	9	3	140LM	3	
12W/350mA LED Driver	120V	.350mA	3	3	12	1	80LM	3	
16.8W/350mA LED Driver	120V	.350mA	7	8	16	1	80LM	8	
24W/700mA LED Driver	120V	.700mA	7	7	24	3	140LM	7	
	8W/350mA LED Driver 9W/700mA LED Driver 12W/350mA LED Driver 16.8W/350mA LED Driver	8W/350mA LED Driver 120V 9W/700mA LED Driver 120V 12W/350mA LED Driver 120V 16.8W/350mA LED Driver 120V	8W/350mA LED Driver 120V .350mA 9W/700mA LED Driver 120V .700mA 12W/350mA LED Driver 120V .350mA 16.8W/350mA LED Driver 120V .350mA	Description Input Input Current Minimum 8W/350mA LED Driver 120V .350mA 1 9W/700mA LED Driver 120V .700mA 1 12W/350mA LED Driver 120V .350mA 3 16.8W/350mA LED Driver 120V .350mA 7	Description Input Input Current Minimum Maximum 8W/350mA LED Driver 120V .350mA 1 6 9W/700mA LED Driver 120V .700mA 1 3 12W/350mA LED Driver 120V .350mA 3 3 16.8W/350mA LED Driver 120V .350mA 7 8	Description Input Input Current Minimum Maximum Wattage 8W/350mA LED Driver 120V .350mA 1 6 8 9W/700mA LED Driver 120V .700mA 1 3 9 12W/350mA LED Driver 120V .350mA 3 3 12 16.8W/350mA LED Driver 120V .350mA 7 8 16	Description Input Input Current Minimum Maximum Wattage Puck Light 8W/350mA LED Driver 120V .350mA 1 6 8 1 9W/700mA LED Driver 120V .700mA 1 3 9 3 12W/350mA LED Driver 120V .350mA 3 3 12 1 16.8W/350mA LED Driver 120V .350mA 7 8 16 1	Description Input Input Current Minimum Maximum Wattage Puck Light Output/Fix 8W/350mA LED Driver 120V .350mA 1 6 8 1 80LM 9W/700mA LED Driver 120V .700mA 1 3 9 3 140LM 12W/350mA LED Driver 120V .350mA 3 12 1 80LM 16.8W/350mA LED Driver 120V .350mA 7 8 16 1 80LM	