


#### DIMMENSION

LED







## **3W LED SQUARE PUCK SERIES**

LED-HU-45 is a puck light that can be use for recessed or surface mounted applications. It is designed with a magnetic-adhesive plate for a quick and easy installation. It is a dimmable and eco-friendly. LED-HU-45 is a great replacement for hot halogen lighting. It is the perfect source of light for display lighting, under cabinet, shelf and counter.

| INPUT VOLT. | THD  | INPUT POWER | LUMENS |
|-------------|------|-------------|--------|
| 12          | <20% | 3W(+/-5%)   | 240    |

### **SPECIFICATIONS**

- Dimmable with selected driver (See page 2 for detail driver info)
- CRI: 90+
- 240 Lumens
- 3W Output LED
- 20W Halogen Replacement
- Lens: Diffused Frosted Lens
- Energy savings of 85%
- Great for displays, cabinets & showcases
- Beam Angle: 120° Input Voltage: 12V DC
- Color Temp: 3000K/ 4000K
- Connection: 24" Lead Wire w/ Connector
- Rated Life: 50,000 Hours
- Warranty: 3 Year Limited Warranty

## **ACCESORIES:**



LED-HU-ACC-1-WH (White) LED-HU-ACC-1-BK (Black) 6-port adapter for led-hu-41 and 45





LED-HU-ACC-2-WW (White) LED-HU-ACC-2-WB (Black) 24" extnesion wire to adapter in white, 24" extension wire to driver.

#### **EXAMPLE:** LED-HU-45-LED-240L-30K-90-WH

| SERIES    | LUMENS | CCT            | CRI | FINISH  |  |  |  |
|-----------|--------|----------------|-----|---|--|--|--|
| LED-HU-45 | □ 240L | □ 30K<br>□ 40K | 90+ | <ul><li>□ WH-White</li><li>□ BK-Black</li><li>□ SI-Silver</li></ul> |  |  |  |
| LED-HU-45 |        |                |     |   |  |  |  |
| SERIES    | LUMENS | CCT            | CF  | RI FINISH   |  |  |  |



# **ROUND LED UNDERCABINET**

## NON-DIMMABLE COMPACT LED DC 12V ELECTRONIC LOW VOLTAGE DRIVERS

| TYPE                | Input(277V) | Output |
|---------------------|-------------|--------|
| LED-HU-DR-12V-30W   | 1@30 Watts  | 12V DC |
| LED-HU-DR-12V-60W   | 1@60 Watts  | 12V DC |
| I FD-HU-DR-12V-100W | 1@100 Watts | 12V DC |



## DIMMABLE COMPACT LED DC 12V ELECTRONIC LOW VOLTAGE DRIVERS

NOTE: Hard wire only. Power cable sold separately

| PART#                         | Input(120V) | Output(12V) | Depth | Height | Width |
|-------------------------------|-------------|-------------|-------|--------|-------|
| LED-HU-ELV-DIMTR-DC-12-25-120 | 1@25 Watts  | 12V         | 2.1"  | 0.7"   | 6"    |
| LED-HU-ELV-DIMTR-DC-12-50-120 | 1@50 Watts  | 12V         | 2.5"  | 1"     | 7"    |
| LED-HU-ELV-DIMTR-DC-12-60-120 | 1@60 Watts  | 12V         | 2.3"  | 1.4"   | 7"    |



## **PHASE / TRAIC DIMMER TEST LIST**

| Brand  | Model number<br>(Dimmer) | Input<br>Voltage<br>Range | Compatibility | Dimming<br>Range | Forward<br>Phase or<br>Reserve<br>phase |
|--------|--------------------------|---------------------------|---------------|------------------|---|
|        | SCL-153PR-WH             | 100-130V                  | ОК            | 0-100%           | Forward<br>Phase                        |
|        | DVCL-153PR-WH            | 100-130V                  | ОК            | 0-100%           | Forward<br>Phase                        |
|        | DVWCL-153PH-LA           | 100-130V                  | ОК            | 0-100%           | Forward<br>Phase                        |
|        | CTCL-153PDH-LA           | 100-130V                  | OK            | 0-100%           | Forward<br>Phase                        |
|        | TGCL-153PR-WH            | 100-130V                  | ОК            | 0-100%           | Forward<br>Phase                        |
|        | TGCL-153PH-WH            | 100-130V                  | ОК            | 0-100%           | Forward<br>Phase                        |
|        | MACL-153MH-LA            | 100-130V                  | ОК            | 5-100%           | Forward<br>Phase                        |
|        | CT-600PR-IV              | 100-130V                  | ОК            | 5-100%           | Forward<br>Phase                        |
| 2      | CT-600PR-WH              | 100-130V                  | ОК            | 5-100%           | Forward<br>Phase                        |
| UTRON- | CT-603PGH-WH             | 100-130V                  | ОК            | 9-100%           | Forward<br>Phase                        |
|        | CT-103PR-WH              | 100-130V                  | ОК            | 8-100%           | Forward<br>Phase                        |
|        | DV-600PR-BL              | 100-130V                  | ОК            | 5-100%           | Forward<br>Phase                        |
|        | DV-600PR-WH              | 100-130V                  | ОК            | 4-100%           | Forward<br>Phase                        |
|        | DVW-603PGH-WH            | 100-130V                  | ОК            | 4-100%           | Forward<br>Phase                        |
|        | TG-600PR-LA              | 100-130V                  | ОК            | 8-100%           | Forward<br>Phase                        |
|        | TG-600PR-IV              | 100-130V                  | ОК            | 8-100%           | Forward<br>Phase                        |
|        | TG-600PR-WH              | 100-130V                  | ОК            | 8-100%           | Forward<br>Phase                        |

| Brand   | Model number<br>(Dimmer) | Input<br>Voltage<br>Range | Compatibility | Dimming<br>Range | Forward<br>Phase or<br>Reserve<br>phase |
|---------|--------------------------|---------------------------|---------------|------------------|---|
|         | VPI06-1LZ                | 100-130V                  | ок            | 15-100%          | Forward<br>Phase                        |
| _       | TTI06-1LZ                | 100-130V                  | ОК            | 1-100%           | Forward<br>Phase                        |
| LEVITON | IPL06                    | 100-130V                  | ок            | 15-100%          | Forward<br>Phase                        |
| LEV     | 6672                     | 100-130V                  | ок            | 15-100%          | Forward<br>Phase                        |
|         | TBL03                    | 100-130V                  | ок            | 12-100%          | Forward<br>Phase                        |
|         | 6602                     | 100-130V                  | ок            | 10-100%          | Forward<br>Phase                        |
|         | 6683                     | 100-130V                  | ОК            | 12-100%          | Forward<br>Phase                        |