

Enerlites®

4-HOUR 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06-J



DESCRIPTION

The ENERLITES HET06-J is an in-wall timer switch with 7 buttons. The buttons offer 6 preset countdown times ranging from 5 minutes to 4 hours and one manual ON/OFF button that can override the timer. The timer switch features blue LED indicators with the blue LED flashes twice to indicate success and then stays OFF. This device can work with LED, incandescent, and fluorescent lights as well as fans.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Replace standard light or fan single pole switch
- Sleek design mounts flush with wall plate
- Ground wire required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	6.4A
Tungsten	800W
Electronic Ballast	800VA
Motor	1/4 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Laundry Room
- Pantry
- Basement
- Garage
- Home Spa

SPECIFICATION SUBMITTAL

Job Name

Job Number

Notes

