

54W LED Retrofit Lamp

Order Code: LP18193



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Feature & Benefits

- Energy Saving Replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

Applications

- Post top
- Wallpack
- Area lighting
- · Flood lighting
- Garage lighting
- · General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -40°F and 113°F (-40°C and 45°C)
- Suitable for use in open and enclosed luminaires
- Suitable for use in dry and damp environments
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire
- Lamps have clear polycarbonate cover lenses

For warranty information refer to: www.venturelighting.com/resources/warranties

DLC Model No.: OR8-054BC-EX40K

Product Performance	
Input Power (W)	54
Initial Lumens	7600
Lumens/Watt	140
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours	50000
Min. Lamp Compartment (H x L x W)	16.54" x 8.3" x 8.3" (420mm x 210mm x 210mm)
Dimming	No
Operating Temperature Range	-40°F to 113°F (-40°C to 45°C)
Physical Characteristics	
Base Type	Mogul (EX39)
Overall Length A	9.96" (253mm)
Diameter B	3.35" (85mm)
Weight	1.43 lbs (0.65 kg)
Electrical Characteristics	
Input Voltage Range	100-277V; 50/60Hz
Power Factor	<u>≥</u> 90%
THD	<u>≤</u> 20%
Regulatory Qualifications	
cULus Listed (UL 1993/CSA C22.2 No. 199	93)
cULus Classified (UL 1598C/CSA C22.2 No	o. 250.1)
DLC® Qualified – DLC Model No. OR8-0	54BC-EX40K
Accessories	
SP12714 120-277V Surge Protector	









Revision: 02, 17-Sept 2021

Venture 54W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606

7905 Cochran Road, Suite 300 Glenwillow, Ohio 44139 USA

Email: Venture_Lighting@VentureLighting.com

VentureLighting.com

