



WARNING

WARNING — THE INSTALLATION MUST BE CARRIED OUT BY A QUALIFIED ELECTRICIAN.

1. Read all installation instructions before installing the fixture and keep the attached instruction sheet.
2. This step light is intended for installation in accordance with the National Electric Code (NEC) and local code specifications.
3. The operating voltage range is 9V-15V AC/DC.

Application Notice

TO REDUCE THE RISK OF FIRE, ELECTRIC SHOCK, OR INJURY TO PERSONS, READ THE INSTRUCTIONS BELOW:

1. Keep away from combustibles. Turn OFF / unplug to change lamp. DO NOT touch the lamp and replace after servicing
2. When using multiple luminaires, load is not to exceed the total watts of transformer rating
3. DO NOT operate the LED Deck Light fitted with a missing or damaged shield
4. Install all luminaires 10 feet (3.05m) or more from a pool, spa, or fountain
5. DO NOT touch the lamp directly at any time. Use a soft cloth. Oil from skin may damage the lamp
6. ALWAYS use UL, cUL, and CSA recognized wire connectors for connections
7. DO NOT use extension cords on power units
8. DO NOT touch hot lens, guard, or enclosure

CAUTION

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.

Electrical products can cause death or injury, or damage to property.

If in any doubt about the installation or use of this product, consult a competent electrician.

INSTALLATION

1. Slab Mounting:

1. Use a hammer and chisel to remove the coping stone above the point of application.




Figure (1)

2. Drill two holes in the wall in the place of the two holes of the mounting bracket.




Figure (2)

5. Draw a groove on a wall to prevent the bricks from crushing the cable.




Figure (3)

3. Draw a groove on a wall based on the size of the line diameter.

6. Secure the fixture with the screws through the plastic anchor.




Figure (4)

7. Reseal the wall.




Figure (5)





Figure (6)


2. Light Engine Replacement:

1. Rotate the screw counter-clockwise with a cross screwdriver to remove the replacement LED module.



Remove the replaceable LED Light engine.

2. Rotate the screw clockwise with a cross screwdriver to assemble the replacement LED module.



Assemble the replaceable LED Light engine.

8. Powered on 12V lighting test, connect the input terminal to the 12V power supply input line after test, and make waterproof treatment to prevent leakage.

Wire Connection

Black	Low voltage cable
Black	Low voltage cable